

DIGITAL YEARLY TIMER


müller SC 98.x0 pro4



Accessories



müller FU 20.00 pro



Save'n carry 2.0



müller FU 30.00 pro



Save'n carry
WIN10 App

Overview

- 1, 2, 3 or 4 channels
- Daily, weekly, yearly or astro program
- 300 memory locations
- Integrated Bluetooth
- Programmable via App (iOS, Android and Windows)
- 10 years battery-reserve
- Exchangeable battery (CR 2032)
- Switching capacity 16 A per channel
- Cycle and random function
- Timer function
- External input function (switch or push-button)
- DCF / GPS function
- Extra switching times ON, OFF and pulse by date and time
- Permanent by date and time / holiday function
- Up to 10 special programs possible
- Manual permanent mode
- Manual override
- Fully automatic daylight saving time
- Elapsed time and pulse counter
- Easy handling
- Illuminated display
- Security by PIN-Code

Highlights

- Programmable with PC or Smartphone via Bluetooth (free iOS, Android and Windows app)
- No additional Data stick needed! Bluetooth integrated in time switch
- Exchangeable battery (CR 2032) with 10 years battery reserve
- Random function for presence simulation
- Optimized own consumption: only 0.3 W in „standby“ mode
- Quick and intuitive programming
- Can be programmed with supply disconnected
- Unlimited program security by E2-PROM

Supply voltage versions

- 110-230 V, 50-60 Hz
- 12-24V ACDC see SC 98.20 pro4 / SC 98.40 pro4

Order numbers

■ müller		
SC 98.10 pro4		1 channel version
SC 98.20 pro4		2 channel version
SC 98.30 pro4		3 channel version
SC 98.40 pro4		4 channel version

DIGITAL YEARLY TIMER

müller SC 98.x0 pro4

Technical data

Supply voltage	110-230 V, 50–60 Hz
Voltage tolerance	±15%
Power consumption (real power)	W (depending on the switching status)
Channels (potential-free)	Change-over, contact gap < 3 mm (μ)
Contact material	AgSnO ₂
Switching capacity per channel	
resistive load:	16 A / 250 V~ at cosφ=1
inductive load:	10 A at cosφ=0,6
Min. switching power	1.000 mW (10 V / 10 mA)
Max. starting current	50 A max. 20 ms
Filament Lamp	2.000 W
Halogen Lamp	
Fluorescent Lamp uncompensated	1.000 W
Fluorescent Lamp series compensated	1.000 W
Fluorescent Lamp parallel compensated	550 W
CFL	200 W
LED (230 V~) (LED lamps > 5 W)	200 W
Switching functions	ON OFF pulse cycle extra permanent astro
Pulse length Pulse function (switching time)	00:01 up to 59:59 mm:ss
Pulse length Timer (man. switching)	0:00:01 up to 9:59:59 h:mm:ss
Pulse/Pause length cycle	0:00:01 up to 9:59:59 h:mm:ss
Memory locations	300
Minimum interval	1 Min.
Time base	Quartz DCF (FU 20.00 pro) GPS (FU 30.00 pro)
Quartz accuracy (at 20 °C)	≤ ±0,5 Sec./day (Quartz accuracy optimized for typical ambient conditions)
Power back-up (at 20 °C)	approx. 10 years (exchangeable battery CR 2032)
Program security	unlimited (E ² -PROM)
Display	high resolution LCD (visible area 12,8 cm ²)
Permitted ambient temperature	–30...+55 °C
Housing	self-extinguishing thermoplastic
Dimensions	45 x 71,5 x 58 mm
Mounting	35 mm DIN-rail
Type of connection	Screw terminals (Pull-up type)
Type of protection	IP 20 to DIN EN 60529
Class of protection	II when installed according to regulations
Mode of operation (DIN EN 60730-1)	1 BSTU
Degree of contamination (DIN EN 60730-1)	2
Rated surge voltage (DIN EN 60730-1)	4 kV
Minimum requirement	Android version 5 iOS version 11.0 Bluetooth version 4.1
Accessories (not included in delivery)	Radio receiver DCF FU 20.00 pro Radio receiver GPS FU 30.00 pro

