

MOVEMENT DETECTORS

paladin 773 010 pir



Zubehör



paladin 700 000 pir

Overview

- High sensitivity PIR sensor
- Brightness level and time delay can easily be adjusted via control knobs
- Circular detection area 360°
- Fitted for any lamp loads (LED, RLC, CFL)
- Zero-cross switching for relay-saving switching
- Functional test mode with red LED indicator
- Cover clips for limiting the detection range
- Connect several detectors in parallel to expand the detection area
- Flush-ceiling mounting

- **Optional accessory:**
IR remote control (700 000 pir) for easy and quick setting
(lux, time, sensitivity threshold, manual override)

Order numbers

■ **paladin**

773 010 pir Motion detector for flush-ceiling mounting

MOVEMENT DETECTORS

paladin 773 010 pir

Order information

	EAN	Art. No.
Paladin 773 010 pir	4022709235756	23575

Technical data

Supply voltage	230 V, 50 Hz
Power consumption	< 1 W 16 A / 230 V at cosφ=1
Switching capacity	LED lamps 400 W incandescent & 230V halogen lamps 3000 W LV halogens with electronic transformer 3000 W LV halogens with inductive transformer 2400 W fluorescence 1300 W (130µF) PL lamps 18x7W, 12x11W, 10x15W, 10x20W, 10x23W
Coverage area	360° and Ø 7 m at 2,5 m installed height and 18 °C
Time delay	6 sec. ... 12 min.
Luminosity setting	3 ... 100 lux
Dimensions	Ø 80 mm x 18,5 mm
Mounting	flush-ceiling mounting
Operation temperature range	-10...+45 °C
Connection	screw-type terminals
Protection class	IP 40
Class of protection	II when installed according to regulations

Rights to technical amendments reserved / Technische Änderungen vorbehalten
Droits de modifications techniques réservés / Suscettibile di errori e modifiche

