

## RF SWITCHING ACTUATORS

Switching actuator / blinds actuator paladin 674 730 rf



### Overview

- Switching actuator 2-channels / blind actuator 1-channel
- Functions: Switching 2-channels (on / off), blinds control 1-channel (up / down)
- Breaking capacity 230 V 16 A 50 Hz / 2 x 5 A at  $\cos \varphi=0,5$
- 2 external inputs for additional, wired push buttons
- RF-repeater function included
- Compact housing
- Recessed ceiling mounting
- Protection class IP 20
- KNX-RF compatible

### Order numbers

■ **paladin**

674 730 rf	Switching actuator 2-channels / blinds actuator 1-channel
------------	---

# RF SWITCHING ACTUATORS

## Switching actuator / blinds actuator paladin 674 730 rf

### Technical data

Supply voltage	230 V ~50 Hz
Breaking capacity	250 V / 2 x 16 A at $\cos \varphi=1$ 250 V / 2 x 5 A at $\cos \varphi=0,5$
Transmission type	Codified transmission in 868,4 MHz with ERP>8 mW and a coverage of 100 m (in the free field)
Operating modes	Switching (ON / OFF) Blinds (UP / DOWN)
Permitted ambient temperature	-5°C...+45°C
Dimensions	108 x 52 x 34 mm
Mounting	Recessed ceiling mounting
Connection type	Screw-type terminal
Protection class	IP 20

Rights to technical amendments reserved / Technische Änderungen vorbehalten  
Droits de modifications techniques réservés / Suscettibile di errori e modifiche

